



## EDDIE VAN HALEN SIGNATURE WAH WAH

Congratulations on your purchase of the Eddie Van Halen Signature Wah Wah from Dunlop. Dunlop is the most trusted name in wah pedal manufacturing and the EVH-95 is designed to give you unparalleled sound quality and years of dependable service. Please take a minute to read through this manual so you can get the most out of your EVH-95.

The EVH Wah Wah is the latest offering in the celebrated EVH Signature Series, developed after intensive design collaboration with the legendary guitarist. Early on in the process, Eddie handed over his “Holy Grail” Crybaby—a standard Crybaby customized in the early Nineties with a more vocal-like, High Q inductor and a wider frequency sweep. Amazingly, we found that over the years Eddie’s unique wah style, which uses mostly the middle range of the pedal’s action, had carved his own curve into the pot’s resistive element, making the middle range even more defined and increased the low-end sweep. Our clones of the worn-in pot and hand-selected inductor give the new EVH Wah Wah the same “Holy Grail” feel and tone, and its true hardwire bypass, dual bright blue bypass LEDs, and graphics based on the black and yellow-striped guitar featured on Van Halen II round out this EVH-approved Crybaby with a voice and look all its own.

**Dunlop**

LIVE TO PLAY LIVE®

DUNLOP MANUFACTURING, INC. P.O. BOX 846 BENICIA, CA 94510 U.S.A.

TEL: 1-707-745-2722 FAX: 1-707-745-2658 WWW.JIMDUNLOP.COM

EVH IS A REGISTERED TRADEMARK OF E.L.V.H., INC., USED UNDER LICENSE.  
FRANKENSTEIN ARTWORK © 2004 EDWARD VAN HALEN, USED UNDER LICENSE.

92503004850





CUSTOM WOUND  
EVH INDUCTOR


CUSTOM TAPER EVH  
POTENTIOMETER

CUSTOM EVH  
LOGO TREAD

BLACK AND YELLOW  
VAN HALEN II STRIPED PAINT

BLUE LED INDICATES  
EFFECT ON/OFF  
(ILLUMINATED INDICATES ON)

ADJUSTABLE  
ROCKER TORQUE\*



\*TURN THE ALLEN SCREW  
COUNTER-CLOCKWISE TO LOOSEN  
THE PEDAL; CLOCKWISE TO TIGHTEN.

## POWER

The EVH Wah Wah can be powered by one 9-volt battery (accessed via the bottom of the pedal), a Dunlop ECB-003 AC adapter (ECB-003E in Europe) or a Dunlop DCB-10 DC Brick power supply.

## SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the EVH-95's Instrument jack.
- Run another shielded instrument cable from the EVH-95's Amplifier jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click". Illuminated Blue LED indicates ON.

## TECHNICAL SPECIFICATIONS

- Filter Parameter
  - Low Pass ..... 300Hz ~ 380Hz
  - High Pass ..... 1.9kHz ~ 2.3kHz
- Input Impedance ..... 800K
- Output Impedance ..... 10K
- Bypass ..... True Hard Wired Bypass
- Maximum Input Level ..... -13.5dBV (@ Filter's Center Frequency)
- Maximum Output ..... +6.5dBV
- Maximum Gain (Toe Down) ..... +21dB ..... @ 1.9kHz ~ 2.3kHz
- Maximum Gain (Heel Down) ..... +20dB ..... @ 300Hz ~ 380Hz
- Signal to Noise ..... Heel Down >97dBV, Toe Down >87dBV, 'A' weighted
- Power ..... 2mA @9V DC (18mW no load)

## ADJUSTABLE ROCKER TORQUE

This pedal comes with an adjustable torque clutch that allows the user to control the amount of resistance the rocker has to being moved. The adjustment is located under the rocker at the heel of the pedal. By placing the rocker toe down and looking under the rocker heel, you can see an adjustment allen head screw. By turning this screw clockwise you can increase the rocker torque and conversely, counterclockwise, decreases the rocker torque. Wrench included.